

150WLED BEAM	14CH Mode1	13CH Mode2	DMX Value	Funciton
Dimmer	1	1	0---255	Darkness----->Bright
Dimmer FINE	2		0---255	
Strobe	3	2	0---3 4---103 104---107 108---207 208---212 213---225 226---238 239---251 252---255	Closed Slow Strobe--->Fast Strobe Open Slow Pulsation--->Fast Pulsation Open Random Slow Strobe Random Medium Strobe Random Fast Strobe Open
Color	4	3	0---4 5---8 9---12 13---17 18---21 22---55 26---29 30--- 34 35--- 38 39---42 43---46 47---51 52---55 56---59 60---63 64---68 69---72 73---76 77---81 82---85 86---89 90---93 94---98 99---102 103---179 180---255	WHITE WHITE +Color1 Color1 Color1 +Color2 Color2 Color2 +Color3 Color3 Color3 + Color4 Color4 Color4 + Color5 Color5 Color5+Color6 Color6 Color6 +Color7 Color7 Color7 + Color8 Color8 Color8 + Color9 Color9 Color9 +Color10 Color10 Color10 + Color11 Color11 Color11 + WHITE CW SlowRotation---->Fast Rotation CCW Slow Rotation---->Fast Rotation
Gobo1(Fixed Gobo)	5	4	0---3 4---7 8---11 12---15 16---19	WHITE GOBO 1 GOBO 2 GOBO 3 GOBO 4

			20---23 24---27 28---31 32---35 36---39 40---43 44---47 48---51 52--- 55 56---59 60---63 64---67 68---71 72---113 114---117 118---159 160---166 167---172 173---179 180---185 186--- 191 192---198 199---204 205---211 212---217 218---223 224---230 231---236 237---243 244---249 250---255	GOBO 5 GOBO 6 GOBO 7 GOBO 8 GOBO 9 GOBO 10 GOBO 11 GOBO 12 GOBO 13 GOBO 14 GOBO 15 GOBO 16 GOBO 17 CW SlowRotation----->FastRotation WHITE CCW SlowRotation-----> FastRotation GOBO 2 Shake Slow---->Fast GOBO 3 Shake Slow---->Fast GOBO 4 Shake Slow---->Fast GOBO 5 Shake Slow---->Fast GOBO 6 Shake Slow---->Fast GOBO 7 Shake Slow---->Fast GOBO 8 Shake Slow---->Fast GOBO 9 Shake Slow---->Fast GOBO10 Shake Slow---->Fast GOBO11 Shake Slow---->Fast GOBO12 Shake Slow---->Fast GOBO13 Shake Slow---->Fast GOBO14 Shake Slow---->Fast GOBO15 Shake Slow---->Fast GOBO16 Shake Slow---->Fast
PRISM	6	5	0---127 128--255	EXCLUDED INSERTED
PRISM Rotation	7	6	0---127 128---190 191---194 195---255	Position 0° ---->360° CW FastRotation-----> SlowRotation STOP CCW Slow Rotation----->Fast Rotation
FOCUS	8	7	0---255	
PAN(X)	9	8	0---255	
PAN(X) FINE	10	9	0---255	
TILTE(Y)	11	10	0---255	
TILTE(Y) FINE	12	11	0---255	
P/T SPEED	13	12	0---128 129---170	Fastest----->Slowest Slow Speed (1/3 MaxSpeed)

			171---211 212---255	Medium Speed (1/2 MaxSpeed) Fast Speed (Fastest Speed)
Control	14	13	0---127 128--255	Undefined Reset ALL